2022 IBF Ricoh IM C300 Printer Installation for Windows (macOS > p.5 | Linux > p.7)

1) Download the Ricoh Device Software Manager from the "Utility" tab

2) Install it

http://support.ricoh.com/bb/html/dr_ut_e/re2/model/imc300/imc300.htm

W 0300/0300	F/C400	F/C400SRF		
Important Notice Importan	t			
Your OS				THE SECOND
Microsoft Windows 10 (64-b	oit)			
		∛ Choose o	other OS	
				The second se
_				
ote Before installing, please vis ttps://www.ricoh.com/info/2020/	sit the link below fi /0122_1/	or important information about V	Vindows drivers.	
ote Before installing, please vis ttps://www.ricoh.com/info/2020/ Select driver language	sit the link below fo 0122_1/ English	or important information about V	Vindows drivers.	
ote Before installing, please vis ttps://www.ricoh.com/info/2020/ Select driver language	sit the link below for 122_1/	or important information about V •	Vindows drivers.	Firmware
ote Before installing, please vis ttps://www.ricoh.com/info/2020/ Select driver language Printer Driver Device Software Manager	sit the link below fr 0122_1/ English Utility Ver.2.	or important information about V	Vindows drivers. Fax Utility 9/2022 New!	Firmware
ote Before installing, please vie ttps://www.ricoh.com/info/2020/ Select driver language Printer Driver Device Software Manager Lownload	sit the link below fr 0122_1/ English Utility Ver.2.: This u printer	or important information about V Scanner Driver 20.4.0 Released Date: 24/0 tility searches for available print driver through Internet and inst	Vindows drivers. Fax Utility 9/2022 New! ing devices on the netwo alls it to the PC with the r	Firmware rk, downloads the applicable ninimum operations.

🍂 Device Software Manager Web Installer \times 📌 Setup - Device Software Manager _ X Quality Improvement Program License Agreement Please read the following important information before continuing. SOFTWARE LICENSE AGREEMENT ----YOU, THE END USER, SHALL USE THIS SOFTWARE INCLIDING ANY FUTURE RELEASES, REVISIONS, UPDATES OR ENHANCEMENTS TO THE SOFTWARE (COLLECTIVELY, THE SOFTWARE') ACCORDING TO THE TENDS OR THIS ADDERMENT (THIS ADDERMANT) BY INSTALLING OR USING THE SOFTWARE, OR CLICKING ON THE "ACCEPT" BUTTON, YOU ARE ADDERING TO BE BOUND BY THESE TERMS. IF YOU DO NOT ACCEPT THE TERMS OF THIS AGREEMENT, YOU MAY NOT INSTALL THIS SOFTWARE INTO ANY COMPUTER. Help improve RICOH products. Please select [I will participate in the Quality Improvement Program] if you agree with Quality Improvement Program Grant of License The Software is licensed for use by you for the equipment packaged with the Software or designated by its supplier or us ("Ute Equipment"). You are permitted to use the Software on any computer which permits electronic access to the Equipment. You are not permitted to rent or lesse the Software or to transfer your rights under this license to a third party. We would like you to participate in sending the following information related to your RICOH products to RICOH via the Internet. so that we can plan and develop better products to meet customer needs. Duration The leanse of the Software under this Agreement is effective until terminated. The leanse of the Software under this Agreement will terminate where you fail to comply with the terms of this Agreement. Upon termination. ○ I will participate in the Quality Improvement Program I will not participate in the Quality Improvement Program Run Driver Installer after installation Accept Agreem and Instal View ReadMe after installation Next > Cancel About Cancel



3) Select Network as setup method

Driver Installer		×
Install Steps	Select a setup method	
End User License Agreement	Please select a device interface and then click [Next]. If you want to update the driver on your computer, click [Update Driver].	
Select a setup method	Network	
Devices and Drivers Settings	Make a selection when the PC and the device are connected by the network.	
Install/Update Complete		
	USB Select when the PC and the device are directly connected by a USB cable.	
	Update Driver Updates the driver that is installed on your computer.	
	Back Next Cancel	١.

- 4) Select the IP address of the printer:
- 158.227.41.201 → 1st Floor
- 158.227.41.202 \rightarrow Only for Administration Staff
- 158.227.41.203 → Ground Floor

🤣 Driver Installer				×
Install Steps	Select a device			
End User License Agreement	Select the device to use from t Click [Click if you cannot find th	he list and click [Next]. he device] when specifying the device's If	address.	
Select a setup method	Searching completed.			
Devices and Drivers Settings				Search again
	Device Name	IP Address	Comment	
Select a device	IM C300	158.227.41.201		
	IM C300	158.227.41.202		
Select a device driver	IM C300	158.227.41.203		
Printer Preference				
Install/Update				
Complete				
	Click if you car	nnot find the device		
	Manually enter the settings			
		Back	Next	Cancel

5) The driver will be installed automatically.

🥏 Driver Installer		×
Install Steps	Complete	
End User License Agreement	Add device has succeeded.	
Select a setup method	Report: [Install Result]	^
Devices and Drivers Settings	Add device has successed.	
Install/Update	[Successfully Added Device(s)] RICOH IM C300 PCL 6 -Default Printer:On	
Complete	-Driver:RICOH IM C300 PCL 6 -Version:1.55.0.0 -Port Name:IP_158.227.41.201 -Comment:PCL6 Driver (For Windows) -User Code: -Shared Printer:Off -Added Driver:Volt installed	
	Hudes of Her Hot installed	~
	Successfully Installed Device(s) :	
	RICOH IM C300 PCL 6 V Print Test Page	
		_
	Finish	

6) When finished, go to Windows \rightarrow Settings \rightarrow Devices \rightarrow Printers \rightarrow Select the printer \rightarrow Manage \rightarrow \rightarrow "Printing Preferences" and under the "Basic" tab add your Group Printing Code clicking on the "User Code Setting..." button.

Settings		
命 RICOH IM C300 PCL 6		
Manage your device		Se Get help
Printer status: Idle Open print queue	RICOH IM C300 PCL 6 Printing Pref	ferences ×
Run the troubleshooter Printer properties Printing preferences Hardware properties	Current Setting Current Setting Document Size: Letter (8.5% x11°) Print On: Same as Original Size Reduce/Enlarge: Fit to Paper Size	Job Type: Normal Print Modify User Code Setting Document Size: Copies:(1 to 999) Letter (8.5" x 11") 1 V Print On: Orientation Same User Code Setting User Code Setting ? User Code Setting Input OK Cancel Restore Defaults Help Layout: 0 Off
	Register Current Settings Confirm Tray Settings Settings Summary	Reset All Settings Reset Settings in This Tab OK Cancel Apply Help

2022 IBF Ricoh IM C300 Printer Installation for macOS

1) Download and install the Ricoh IM C300 driver for macOS

http://support.ricoh.com/bb/html/dr_ut_e/re2/model/imc300/imc300.htm

magine. change.		Clos Global - Englis
M C300/C300F/C	400F/C400SRF	
Important Notice Important		
Your OS		- 1
Please choose your OS		00
		0
		and the second second
Before installing, please visit the link ttps://www.ricoh.com/info/2020/0122_1/	below for important information about Windows dr	ivers.
EDDefore installing, please visit the link tips://www.ricoh.com/info/2020/0122_1/ Choose your OS Select driver language Englis	below for important information about Windows dr	vers.
Select installing, please visit the link typs://www.ricoh.com/info/2020/0122_1/ Choose your OS Select driver language Engle Windows	below for important information about Windows dr	Ners.
Selere installing, please visit the link ps://www.riceh.com/info/2020/0122_1/ Choose your OS Select driver language Engli Windows Mac OS X	below for important information about Windows dr	vers.
Selere installing, please visit the link ps://www.ricoh.com/info/2020/01/22_1/ Choose your OS Select driver language Engli Windows Mac OS X Mac OS X Mac OS S (MinacOS Ventura)	below for important information about Windows dr	vers.
Selere installing, please visit the link ps://www.icoh.com/info/2020/0122_1/ Choose your OS Select driver language Engli Windows Mac 06 X Mac 06 X Mac 06 X Mac 06 S Language Select Selectars) Mac 06 12(mac06 Monterey)	below for important information about Windows dr	vers.
Seletre installing, please visit the link ps://www.icoh.com/info/2020/0122_1/ Choose your OS Select driver language Engli Windows Mac 06 X Mac 06 X Mac 06 X Mac 06 S Ventura)	below for important information about Windows dr	vers.
Selere installing, please visit the link ps://www.icoh.com/info/2020/0122_1/ Choose your OS Select driver language Engli Windows Mac OS X Mac OS X Mac OS X Mac OS StaffinacOS Ventura) Mac OS 12(macOS Monterey) Printer Driver PPD Installer	below for Important Information about Windows dr ah • • Wer 13.0.0 Released Date: 0.0022020	vers.

2) Go to System Preferences \rightarrow Printers and add a new one clicking in the + button.



3) Select the "world" icon and enter the IP address the printer, a name for it and click on "Add":

158.227.41.201 \rightarrow 1st Floor

158.227.41.203 → Ground Floor

••• < > !!!! Impre	Añadir impresora
Impresoras	
0 - Ricoh • En espera	
1 - Ricoh • En espera	Dirección: 158.227.41.201 Nombre o dirección de host completa y válida.
Adm - Ricoh En espera, última usada	Protocolo: Protocolo IPP (Internet Printing Protocol)
+ -	Nombre: Ricoh 1st Floor Ubicación:
	Usar: RICOH IM C300 PS
	? Añadir

4) When finished, try to print something and in the printer preferences dialog, select show details at the bottom (if not selected), go to Job Log, activate the User code and add your group user code. You can save this code as a preset to avoid entering the code every time you print something.

From macOS 13 (Ventura) on the JobLog Menu could be found in the Printers Options submenu (right picture)

I de 1 Impresora Preajustes	0 - Ricoh Ajustes por omisión		Impresora	📫 1 - Ricoh 🗘
Copias	: 1 🗘 🗘 🗹 A doble cara		Preajustes	Últimos ajustes utilizados 💲
Páginas	Desde: 1 hasta: 1		1 página por hoja	
Tamaño del papel Orientación	: A4 210 x 297 mm 🙁		> Gestión del papel Intercalar hojas, Todas las hojas	
Regi	stro de trabajos ;		> Opciones de impresora	
ID U	suario:		Ajuste de color	(i)
Tipo de tr Nombre de a	rabajo: Impresión normal 💿	Página 1 de 1	Alimentador de papel	(j)
Contr	aseña:		Características	(j)
Código u	Activar código de usuario suario: XXXX		Registro de trabajos	(j)
	Establecer hora impr		Prevención de copia no autorizada	(j)
Número de la c	arpeta: 0		Detalles de balance de color	(j)
Contraseña de la ca	arpeta:		Numeración de fondo	(j)
			Autenticación de usuario	(1)
? Ocultar detailes PDF 🔍	Cancelar Imprimir		? PDF v	Cancelar Imprimir

2022 IBF Ricoh IM C300 Printer Installation for Linux

1) Open a web browser and enter the following address:

http://localhost:631

(If the webpage asks at any moment for a username and password, you should enter your computer username and password)

2) Go to "Administration" \rightarrow "Add Printers" \rightarrow And select "AppSocket/HP JetDirect" \rightarrow Enter the Printer IP as follows:

socket://158.227.41.201 → 1st Floor

socket://158.227.41.202 \rightarrow Only for Administration Staff

socket://158.227.41.203 → Ground Floor

	s Provescea	× ⊗ ⊛ ⊗ φ] 0 ≡		 ○ @ # # ○ 0 #
CUPS 2.4.1 CUPS est statema de impressión de código abiento basado en estándares desa CUPS para usuarios	erolado por CperPiretry para nacOS" y otros sistemas operativos topo UNIX". CUP CUPS para administradores	Sues IP Derysher" to apport printing to local and network printers.	Agministracion Impresoras Intervente la della de	Servidor (the white its infrared)
Description de CDPS Trepretion deside la linea de contrantes y optimes	Andre Impensions y classes Coaction de performant Date de Impresonas de red Frendrik Referencia de capat cant	CdFB Pogening Moral	Clases Internet Control Contro	Configuration data and and an an an an an and an and an and an and an and an an



3) Write a Name for the Printer \rightarrow Select the brand of the printer (Ricoh) \rightarrow Select the model ("Ricoh IM C300 PDF (EN)"). If not in the list, download the PPD file from here and load it:

https://www.openprinting.org/printer/Ricoh/Ricoh-IM_C300

	EMathimmena CRT X + V X
OpenPrinting CUPS India Administration Classes Apuda Tatalque Impresorae	OperPrinting CLIPS Incise Administration Classes Ayuda Trabajas Impresoras
Añadir impresora	Añadir impresora
Añadir impresora	Añadir impresora
Note: The second	Service (2 +) Benjamin (2 +) Constraint (2 +)
SIF inter SIF and game & Mits Sams And SIF Of Flams Taxanamanan	and - cause of the mount of the Marca and State Parking in Name and an and
● ■Matringenou-CUE: X + V © ® ® ®	Madringeneer-ODF X
	← → Ø 0.0 kañesta hata hata and an
Upenning una montania cale a secon relation a secon relation a secondaria a	uperpring units not with an automatical units water interests
Anadir Impresora	Anduir Impresora
Anadir Impresora	Anadir Impresora
Representation of the second s	for he deale and also a popular. B ^{or} -

4) After the installation go to Administration \rightarrow Admin Printers \rightarrow Select the Printer \rightarrow Set Predefined Setups \rightarrow JCL (or Job Log) \rightarrow Select "User Code (up to 8 digits): Custom UserCode" \rightarrow Write your Group Printers Code \rightarrow Change predefined Setups

A A C C		A C D Redbat at the set of the control					• •	
OpenPrinting CLIPS Inice Administración Disses Ayuda Trabajos Impresonas	u v -	OpenPrinting CUPS Inicia Administración Clases o	Ayuda Trabajos Impresoras					
Administración		Impresoras						
		mpreserus						
Impresoras	Servidor		Buscar en imp	Nostrando 1 de 1 impresora	(Buscar) (Borrar)			
Alafri menesira Encontrar susual internet Administrar internetia	Editar archive de confessariale	recención de la cola	Descripción	Ubicación	Marca y modelo	Estado		
Clases	Configuración del servidor:	187-1			Ricoh IM C300 PDF	inactiva		
Clases	Avanzada Compartir interespons conscilatos a este sistema							
Adadr class Administrar classs	Permitr la impresión desde Internet Providir administración emota							
Trabajos	Usar autentificación Kerberos (FAG) Permitir a los usuarios cancelar cualquier trabaio (no sólo los suvos propios)							
Administrar trabajos	Guardar información de depuración para búsqueda de problemas							
	Canbiar configuración							
COPE or allows as COPE can manual maintains as Andrine Denotes do and a 2007-2011 South Inst Texture as Annotation manuality.		And a close in And on some existing in how to family in Andrew Stational	ter Tala in desider menaler					
a marine and a								
		Cambiar opciones impre × +					V (6)	
OpenPhinting CUPS Incle Administración Clases Ayuda Trabajos Impresoras	u • -	ComPleting CUPS Inicial Administración Clases	Avda Trabaica Impresoras					0 -
IBF-1		Cambiar opciones impresora						
IBF-1 (inactiva, aceptando trabajos, no compartida)		Establecer opciones predetermin	adas de IBF-1					
Mantanimianta v administration v		Opciones instaladas JCL Basic	Paper Finishing	Print Quality Effects	Job Log Color Balance Details	Rótulos R	eglas	
Descripcic Administration Ubicacid Modificar Increases								
Controla domar impressora				PageSize: A4 (210 x 297 r	ani v			
Opciones predeterminas autor concentration of content				InputSiol: Auto Select v				
Trabajos				Collate: 9 Of O On				
Buscar en 100-1:	Burger Borrar			Color Mode: Color Paper Type: mice Tenented				
Mostrar trubajos completados Mostrar todos los trabajos				Destination: Printer Default	v			
Active jobs listed in process	sing order • ; held jobs appear first.			Resolution: 600 (pl v Gradation: Countert v				
				Print Mode: or	0			
				Decound (1.8 diality)				
				User Code (up to 8 digits): Custom UserCo UserCode:	de v			
		U	iser ld (Up to 8 alphanumeric (a	FZA-Z,9-9,-U: Characters(: User1				
				Canthiar opciones predeterminada	3			
				Canthiar opcisnes predeterminado				